



# Power Factor Controller BR6000-T Version 5.0

Power Quality Solutions  
Key Components for  
Power Factor Correction

The BR6000-T power factor controller is designed especially for dynamic PFC where capacitors are switched by thyristor modules. Its very fast processor allows extremely short switching times to be achieved – mandatory when dealing with fast-changing loads (min. switching time 20 ms).

Applications for dynamic PFC

- Welding/spot welding equipment
- Machine presses
- Wind turbine generators
- Container cranes
- Elevators
- Motor start up compensation
- Any fast changing load

## BR6000-T front panel controls

- Operating mode
- Automatic
  - Programming
  - Manual operation
  - Service
  - Expert mode



- Enter / OK  
Confirm and store values



- Increase selected parameter



- Reduce selected parameter



### Features and benefits

- 6 and 12 steps available
- Intelligent control
- Menu-driven user interface in plain language (Czech/Dutch/English/French/German/Polish/Portuguese/Russian/Spanish)
- Large multifunctional LCD (2 x 16 characters), graphic and alphanumeric
- Display of
  - System voltage (V AC)
  - Reactive power (kvar)
  - Active power (kW)
  - Frequency
  - Apparent power (kVA)
  - Apparent current (A)
  - Temperature (°C)
  - Real-time  $\cos \varphi$
  - Target  $\cos \varphi$
  - kvar value to target  $\cos \varphi$
  - Programmable 2<sup>nd</sup> alarm relay
- Alarm output:
  - Insufficient compensation
  - Overcompensation
  - Undercurrent
  - Overcurrent
  - Overtemperature
  - Programmable threshold value
  - Internal error storage
- Direct triggering of TSM series of thyristor modules
- Self-optimizing control capability
- Enhanced operating voltage range from 110 to 230 V AC
- Enhanced measuring voltage range from 30 to 525 V AC
- Recall function of recorded values
- Four-quadrant operation (e.g. standby generator)
- Powerful alarm output
- 2<sup>nd</sup> parameter set available
- 20 pre-programmed control series and control series editor
- Detailed expert modes
- Detailed fault messages
- Manual / automatic operation
- RS485 interfaces optional

### Available versions and ordering codes:

BR6000-T6	6 transistor outputs, 1 relay output	B44066R6106E230
BR6000-T12	12 transistor outputs, 1 alarm relay, 1 additional user programmable message relay, input for second parameter set	B44066R6112E230
BR6000-T12/S485	additional RS485 interface	B44066R6412E231

**Important information:** Some parts of this publication contain statements about the suitability of our products for certain areas of application. These statements are based on our knowledge of typical requirements that are often placed on our products. We expressly point out that these statements cannot be regarded as binding statements about the suitability of our products for a particular customer application. It is incumbent on the customer to check and decide whether a product is suitable for use in a particular application. This publication is only a brief product survey which may be changed from time to time. Our products are described in detail in our data sheets. The Important Notes ([www.epcos.com/ImportantNotes](http://www.epcos.com/ImportantNotes)) and the product-specific warnings and cautions must be observed. All relevant information is available through our sales offices.